



A.H. Systems, Inc.

9710 Cozycroft Ave.
Chatsworth, CA 91311



Tel: (818) 998-0223

Fax: (818) 998-6892

◆ sales@AHSystems.com

◆ www.AHSystems.com



BCP-614

Broadband Current Probe

10 KHz – 300 MHz

This current probe measures high power pulse currents such as those associated with EMP wave shapes. It clamps around large conductors or bundles of wire and has an aperture of 2.6".

Frequency Range: 10 KHz - 300 MHz

Transfer Impedance (dBΩ) -25 to 2

Max Cont. Current (Amps) 350 (DC to 400 Hz)

Connector: N-Type, Female

Physical Dimensions

Aperture: 2.6" (66 mm)

Diameter: 4.27" (134 mm)

Weight: 5.5 lb.'s (2.5 kg)

Features

- High current conducted emissions measurements without saturation.
- Ideally suited to measuring currents on large cables.
- Individually Calibrated (Transfer Impedance calibration included)
- Split Type Clamp-on Design
- Three Year Warranty

The BCP-514 measures high power pulse currents such as those associated with EMP wave shapes. This current probe is designed to clamp around large conductors or bundles of wire with an aperture of 2.6" (66 mm).

Recommended Accessories

- CPF-630 Current Probe Fixture
- SAC-213 N/N Cable, 3 Meter



A.H. Systems, Inc.

9710 Cozycroft Ave.
Chatsworth, CA 91311



Tel: (818) 998-0223
Fax: (818) 998-6892

◆ sales@AHSystems.com
◆ www.AHSystems.com

**Broadband Current Probe
Calibration
Model: BCP-614**

Transfer Impedance Conversion Formula:

$$\text{dB}\mu\text{A} = \text{dB}\mu\text{V} - \text{dB}\Omega + \text{cable loss}$$

